

PL77/L77F-UCD9(USD6+CAD3)

PL77/L77F DIP SWITCHES SETTING : 1(Pulse/ccTalk/ICT104U)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.
CAD 5, 10, 20 3bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / USD 1	OFF	OFF	OFF							
	2 Pulse / USD 1	OFF	OFF	ON							
	3 Pulse / USD 1	OFF	ON	OFF							
	4 Pulse / USD 1	OFF	ON	ON							
	5 Pulse / USD 1	ON	OFF	OFF							
	10 Pulse / USD 1	ON	OFF	ON							
	20 Pulse / USD 1	ON	ON	OFF							
	100 Pulse / USD 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept USD 1 & 5						ON				
	Reject USD 1 & 5						OFF				
★	Accept USD 10 & 20							ON			
	Reject USD 10 & 20							OFF			
	Accept USD 50 & 100								ON		
★	Reject USD 50 & 100								OFF		
★	Accept CAD 5 & 10 & 20									ON	
	Reject CAD 5 & 10 & 20									OFF	
★	Accept USD + CAD										ON
	Accept only CAD										OFF

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

(3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

PL77/L77F-UCD9(Pulse/ccTalk/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
	ICT104U Mode		ON	ON	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccTalk)

	FUNCTION	SW1	SW2	SW3	SW4
	8-bit checksum	ON			
★	CRC 16-bit checksum	OFF			
	Pulse Mode		ON	OFF	
★	ccTalk Interface		OFF	OFF	
	ICT104U Mode		ON	ON	
	ccTalk Parameters Restore Switch Please see "Note" for detail		OFF	ON	
★	Encryption Mode				ON
	Decrypt Mode				OFF

★ Manufacture setting

Note: Put this switch to on and reset power will restore the ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	ccTalk Interface		OFF	OFF	
★	ICT104U Mode		ON	ON	
	Reserved		OFF	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	ccTalk
BV1	USD 1	USD 1	USD 1
BV2	USD 5	USD 5	USD 5
BV3	USD 10	USD 10	USD 10
BV4	USD 20	USD 20	USD 20
BV5	USD 50	USD 50	USD 50
BV6	USD 100	USD 100	USD 100
BV7	CAD 5	CAD 5	CAD 5
BV8	CAD 10	CAD 10	CAD 10
BV9	CAD 20	CAD 20	CAD 20