

XBA mini-UMR12(USD6+MYR6)

XBA mini Option Switch Settings: 1(Pulse/ICT104U)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.
Supported bill MYR 1, 5, 10, 20, 50, 100 6bills.

XBA mini dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject USD 1 & 5 & 10	ON											
	Accept USD 1 & 5 & 10	OFF											
★	Reject USD 20 & 50		ON										
	Accept USD 20 & 50		OFF										
★	Reject USD 100			ON									
	Accept USD 100			OFF									
★	Reject MYR 1 & 5 & 10				ON								
	Accept MYR 1 & 5 & 10				OFF								
★	Reject MYR 20 & 50 & 100					ON							
	Accept MYR 20 & 50 & 100					OFF							
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★	Stack Banknote when Power-up							ON					
	Reject Banknote when Power-up							OFF					
★	Reserved								ON				
	Reserved								OFF				
★	Inhibit Active High									ON			
	Inhibit Active Low									OFF			
★	Reserved										ON		
	Reserved										OFF		
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : 1. After setting dip switch of the credit pulses,you should reset the bill acceptor again.
2. Calibration card is needed.
3. Pulse Mode: USD 1=MYR 5

XBA mini-UMR12(Pulse/ICT104U)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	ICT104U Mode		OFF		
★	1 pulse / MYR 1			OFF	OFF
	2 pulses / MYR 1			OFF	ON
	5 pulses / MYR 1			ON	OFF
	10 pulses / MYR 1			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U	Interface Bill value	Pulse	ICT104U
BV1	MYR 1	MYR 1	BV7	USD 1	USD 1
BV2	MYR 5	MYR 5	BV8	USD 5	USD 5
BV3	MYR 10	MYR 10	BV9	USD 10	USD 10
BV4	MYR 20	MYR 20	BV10	USD 20	USD 20
BV5	MYR 50	MYR 50	BV11	USD 50	USD 50
BV6	MYR 100	MYR 100	BV12	USD 100	USD 100

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
	ICT104U Mode		OFF		
★	Reserved			ON	
	Reserved			OFF	
★	Reserved				ON
	Reserved				OFF

★ Manufacture setting