

BRV-MXN9(MXN5+USD4)

BRV Option Switch Settings: 1(ICT-BC/MDB/JPSTD Dummy)

Supported bill MXN 20, 50, 100, 200, 500 5bills. USD 1, 5, 10, 20 4bills.

BRV dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
Reject USD 1	ON											
Accept USD 1	OFF											
Reject MXN 50 & USD 5		ON										
Accept MXN 50 & USD 5		OFF										
Reject MXN 100 & USD 10			ON									
Accept MXN 100 & USD 10			OFF									
Reject MXN 200/500 & USD 20			ON									
Accept MXN 200/500 & USD 20			OFF									
Reject MXN 20				ON								
Accept MXN 20				OFF								
Normal					OFF	OFF						
Load Banknote to Recycle					ON	OFF						
Load Banknote to Stacker					OFF	ON						
Unload Banknote to Stacker					ON	ON						
Accept Mexico Pesos and US Dollars (Note.3)								ON				
Accept Mexico Pesos Only (Note.3)								OFF				
MDB Mode	SW1	SW2	SW3	SW4	JPSTD Dummy Mode							
Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON				
Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF				
Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF				
Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF				
Reserved			ON		4 Bank Note Limitation Per Transaction	ON	ON	OFF				
Reserved			OFF		5 Bank Note Limitation Per Transaction	OFF	OFF	ON				
Reserved				ON	6 Bank Note Limitation Per Transaction	ON	OFF	ON				
Reserved				OFF	7 Bank Note Limitation Per Transaction	OFF	ON	ON				
Virtual MDB Recycler Function (Note.5)				ON	No Refund After the Deal						ON	
Standard MDB Recycler Function				OFF	★ Refund After the Deal						OFF	

★ Manufacture setting

- Note : (1) After setting dip switch of the credit pulses,you should reset the bill acceptor again.
 (2) Please reset the bill acceptor after set the dip switch.
 (3) For Accepting US Dollars, make sure you have dip 8 set to ON position.
 (* Exchange Rate on USD to MXN is 1:18 for MDB,ICT-BC Mode)
 (4) Calibration card is needed.
 (5) Recycled Banknote represents virtual MDB coin type.

BRV-MXN9(MXN5+USD4)(ICT-BC/MDB/JPSTD Dummy)

Interface Settings: 2(ICT-BC)

INTERFACE	SW5	SW6	SW7	SW8
Reserved	ON			
Reserved	OFF			
Connect with MDB Connector		ON		
Connect with RS232 Connector		OFF		
MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
Reserved			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(JPSTD Dummy)

INTERFACE	SW5	SW6	SW7	SW8
Escrow (JPSTD Dummy Mode)	ON			
No Escrow (JPSTD Dummy Mode)	OFF			
Reserved		ON		
Reserved		OFF		
MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
Reserved			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

INTERFACE	SW5	SW6	SW7	SW8
Scaling Factor (SF)= 100 Decimal Point Position (DPP)= 2	ON			
Scaling Factor (SF)= 1 Decimal Point Position (DPP)= 0	OFF			
Reserved		ON		
Reserved		OFF		
MDB Mode			OFF	OFF
JPSTD Dummy Mode			OFF	ON
Reserved			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	JPSTD Dummy	ICT-BC	MDB	Recycler banknote inventory	
BV1	MXN 20	MXN 20	MXN 20	MXN 20	25 pcs
BV2	MXN 50	MXN 50	MXN 50	MXN 50	25 pcs
BV3	MXN 100	MXN 100	MXN 100	MXN 100	25 pcs
BV4	MXN 200	MXN 200	MXN 200	MXN 200	25 pcs
BV5	MXN 500	MXN 500	MXN 500	MXN 500	25 pcs
BV6	USD 1	USD 1	USD 1	USD 1	25 pcs
BV7	USD 5	USD 5	USD 5	USD 5	25 pcs
BV8	USD 10	USD 10	USD 10	USD 10	25 pcs
BV9	USD 20	USD 20	USD 20	USD 20	25 pcs