

L70+USD6

L70+/P5 DIP SWITCHES SETTING : 1(110V Pulse/ICT104U/ICT104V/MDB)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / USD 1	OFF	OFF	OFF							
	2 Pulse / USD 1	OFF	OFF	ON							
	3 Pulse / USD 1	OFF	ON	OFF							
	4 Pulse / USD 1	OFF	ON	ON							
	5 Pulse / USD 1	ON	OFF	OFF							
	10 Pulse / USD 1	ON	OFF	ON							
	20 Pulse / USD 1	ON	ON	OFF							
	100 Pulse / USD 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept USD 1				ON						
	Reject USD 1				OFF						
★	Accept USD 5				ON						
	Reject USD 5				OFF						
★	Accept USD 10				ON						
	Reject USD 10				OFF						
★	Accept USD 20				ON						
	Reject USD 20				OFF						
★	Accept USD 50 & 100				ON						
	Reject USD 50 & 100				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70+USD6(110V Pulse/ICT104U/ICT104V/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	ICT104V
BV1	USD 1	USD 1	USD 1	USD 1
BV2	USD 5		USD 5	USD 5
BV3	USD 10	USD 5	USD 10	USD 10
BV4	USD 20	USD 10	USD 20	USD 20
BV5	USD 50	USD 20	USD 50	USD 50
BV6	USD 100	USD 50	USD 100	USD 100
BV7		USD 100		

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104V)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	MDB Mode		ON	ON	
★	ICT104V Mode		OFF	OFF	
★	Reserved				ON OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
★	MDB Mode		ON	ON	
	ICT104V Mode		OFF	OFF	
★	Reserved				ON OFF

★ Manufacture setting