

S7ER-USD6 Option Switch Settings: (Pulse)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.

S7ER dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
★	Reject USD 1	ON															
★	Accept USD 1	OFF															
★	Reject USD 5		ON														
★	Accept USD 5		OFF														
★	Reject USD 10			ON													
★	Accept USD 10			OFF													
★	Reject USD 20				ON												
★	Accept USD 20				OFF												
★	Reject USD 50 & 100					ON											
★	Accept USD 50 & 100					OFF											
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
★	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
★	Stack Banknote when Power-up							ON									
★	Reject Banknote when Power-up							OFF									
★	Inhibit Active HIGH								ON								
★	Inhibit Active LOW								OFF								
★	Pulse Speed	100ms LO / 100ms HI							ON								
★		50ms LO / 50ms HI							OFF								
★	Reserve									ON							
★										OFF							
★	Reserve										ON						
★											OFF						
★	Reserve											ON					
★												OFF					
★	Credit-Pulse Normal HIGH												ON				
★	Credit-Pulse Normal LOW												OFF				
★	Pulse Mode													ON			
★	ICT002 Mode													OFF			
★	1 pulse / USD 1														OFF	OFF	
★	2 pulses / USD 1															OFF	ON
★	4 pulses / USD 1															ON	OFF
★	20 pulses / USD 1															ON	ON

★ Manufacture setting

Note: After setting dip switch of the credit pulses, you should reset the bill acceptor again.

S7ER-USD6 (ICT002)

S7ER dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
★	Reject USD 1	ON															
★	Accept USD 1	OFF															
★	Reject USD 5		ON														
★	Accept USD 5		OFF														
★	Reject USD 10			ON													
★	Accept USD 10			OFF													
★	Reject USD 20				ON												
★	Accept USD 20				OFF												
★	Reject USD 50 & 100					ON											
★	Accept USD 50 & 100					OFF											
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
★	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
★	Stack Banknote when Power-up							ON									
★	Reject Banknote when Power-up							OFF									
★	Test Mode (No Communication)								ON								
★	Operation Mode								OFF								
★	Reserved									ON							
★										OFF							
★	Reserved										ON						
★											OFF						
★	Reserved											ON					
★												OFF					
★	Reserved												ON				
★													OFF				
★	Reserved													ON			
★	Reserved													OFF			
★	Pulse Mode														ON		
★	ICT002 Mode														OFF		
★	Reserved															ON	
★	Reserved															OFF	
★	Reserved																ON
★	Reserved																OFF

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note: 1.No RFID function.

Currency Assign Data

Interface Bill value	Pulse	ICT002
BV1	USD 1	USD 1
BV2	USD 5	USD 5
BV3	USD 10	USD 10
BV4	USD 20	USD 20
BV5	USD 50	USD 50
BV6	USD 100	USD 100