

TAO-A-USD6

TAO-A Option Switch Settings: 1(Pulse+NISR+ICT002U+5V Enable+Out of Service+RS232 A0)

Supported bill USD 1, 5, 10, 20, 50, 100 6 bills.

TAO-A dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject USD 1	ON											
★	Accept USD 1	OFF											
	Reject USD 5		ON										
★	Accept USD 5		OFF										
	Reject USD 10			ON									
★	Accept USD 10			OFF									
	Reject USD 20				ON								
★	Accept USD 20				OFF								
	Reject USD 50 & 100				ON								
★	Accept USD 50 & 100				OFF								
	Auto Detection SEND Signal (NISR Mode only)					ON							
★	Normal High SEND Signal (NISR Mode only)					OFF							
	Pulse Mode	Other Mode											
	Harness Disable	BA stops working when fishing					ON						
★	Harness Enable	Normal					OFF						
	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 pulse / USD 1								OFF	OFF			
	2 pulses / USD 1								ON	OFF			
	4 pulses / USD 1								OFF	ON			
	20 pulses / USD 1								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

- ◆ Note: 1.Reset the bill acceptor after setting the dip switch.
2.SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.
3.Pulse mode has out of service function.

Currency Assign Data

Interface Bill value	Pulse	ICT	NISR	RS232 A0
BV1	USD 1	USD 1	USD 1	USD 1
BV2	USD 5	USD 5		
BV3	USD 10	USD 10	USD 5	USD 5
BV4	USD 20	USD 20	USD 10	USD 10
BV5	USD 50	USD 50	USD 20	USD 20
BV6	USD 100	USD 100	USD 50	USD 50
BV7			USD 100	USD 100

TAO-A-USD6(Pulse+NISR+ICT002U+5V Enable+Out of Service+RS232 A0)

Interface Settings: 2(ICT002U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	ICT002U Mode		ON	ON	
	NISR Mode		OFF	ON	
	Pulse Mode		ON	OFF	
	5V Enable Mode		OFF	OFF	
	RS232 A0 Mode				ON
★	Other Mode				OFF

★ Manufacture setting

Interface Settings: 2(NISR)

	INTERFACE	SW1	SW2	SW3	SW4
	No ERROR CODE	ON			
★	Send ERROR CODE	OFF			
	ICT002U Mode		ON	ON	
★	NISR Mode		OFF	ON	
	Pulse Mode		ON	OFF	
	5V Enable Mode		OFF	OFF	
	RS232 A0 Mode				ON
★	Other Mode				OFF

★ Manufacture setting

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
	ICT002U Mode		ON	ON	
	NISR Mode		OFF	ON	
★	Pulse Mode		ON	OFF	
	5V Enable Mode		OFF	OFF	
	RS232 A0 Mode				ON
★	Other Mode				OFF

★ Manufacture setting

Interface Settings: 2(5V Enable)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
	ICT002U Mode		ON	ON	
	NISR Mode		OFF	ON	
	Pulse Mode		ON	OFF	
★	5V Enable Mode		OFF	OFF	
	RS232 A0 Mode				ON
★	Other Mode				OFF

★ ★ Manufacture setting

Interface Settings: 2(RS232 A0)

	INTERFACE	SW1	SW2	SW3	SW4
	Reserved	ON			
★	Reserved	OFF			
	Reserved		ON		
★	Reserved		OFF		
	Reserved			ON	
★	Reserved			OFF	
★	RS232 A0 Mode				ON
	Other Mode				OFF

★ Manufacture setting

RS232 A0 INFORMATION

BillType Data	
Code	Denomination
1	USD 1
2	Reserved
3	USD 5
4	USD 10
5	USD 20
6	USD 50
7	USD 100
8	Reserved