

TAO-A.V-MXN9(MXN5+USD4)

TAO-A.V Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill N\$ 20, 50, 100, 200, 500 5bills.
USD 1, 5, 10, 20 4bills.

TAO-V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject N\$ 20 & USD \$1	ON											
★	Accept N\$ 20 & USD \$1	OFF											
★	Reject N\$ 50 & USD \$5		ON										
★	Accept N\$ 50 & USD \$5		OFF										
★	Reject N\$ 100 & USD \$10			ON									
★	Accept N\$ 100 & USD \$10			OFF									
★	Reject N\$ 200/500 & USD \$20				ON								
★	Accept N\$ 200/500 & USD \$20				OFF								
★	Accept Mexico Pesos and US Dollars (Note.3)				ON								
★	Accept Mexico Pesos Only (Note.3)				OFF								
★	Reserved				ON								
★	Reserved				OFF								
	Pulse Mode	Other Mode											
★	Harness Disable	BA stops working when fishing					ON						
★	Harness Enable	Normal					OFF						
★	Inhibit Active High						ON						
★	Inhibit Active Low						OFF						
★	1 pulse / N\$ 10 / USD \$1							OFF	OFF				
★	2 pulses / N\$ 10 / USD \$1							ON	OFF				
★	5 pulses / N\$ 10 / USD \$1							OFF	ON				
★	10 pulses / N\$ 10 / USD \$1							ON	ON				
★	Interface Timing Conversion	50ms HI / 50ms LO								OFF	OFF		
		300ms HI / 60ms LO								ON	OFF		
		50ms HI / 30ms LO								OFF	ON		
		150ms HI / 150ms LO								ON	ON		

★ Default setting

Use 2nd dip switch of the internal dip-switch to change different interface protocol.

◆ Note : (1) Default setting

(2) Use 2nd dip switch of the internal dip-switch to change different interface protocol.

(3) For Accepting US Dollars, make sure you have dip 5 set to ON position.

(* Exchange Rate on USD to MXN is 1:18 for MDB Mode)

Appendix

TAO-A.V-MXN9(MXN5+USD4)(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	ICT104V Mode		ON	ON	
	MDB Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse	MDB	ICT104V
BV1	USD \$1	USD \$1	USD \$1	USD \$1
BV2	N\$ 20	N\$ 20	N\$ 20	N\$ 20
BV3	N\$ 50	N\$ 50	N\$ 50	N\$ 50
BV4	N\$ 100	N\$ 100	N\$ 100	N\$ 100
BV5	N\$ 200	N\$ 200	N\$ 200	N\$ 200
BV6	N\$ 500	N\$ 500	N\$ 500	N\$ 500
BV7	USD \$5	USD \$5	USD \$5	USD \$5
BV8	USD \$10	USD \$10	USD \$10	USD \$10
BV9	USD \$20	USD \$20	USD \$20	USD \$20

Interface Settings: 2(ICT104U/ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	ON	
	ICT104V Mode		ON	ON	
	MDB Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

★ Manufacture setting

TAO-V-MXN9(MXN5+USD4)

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	ON	
	ICT104V Mode		ON	ON	
★	MDB Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting