

V7-USD4

V7 Option Switch Settings: 1 (Pulse/ICT004/MDB)

Supported bill USD 1, 5, 10, 20 4bills.

V7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject USD 1	ON											
★	Accept USD 1	OFF											
	Reject USD 5		ON										
★	Accept USD 5		OFF										
	Reject USD 10			ON									
★	Accept USD 10			OFF									
	Reject USD 20				ON								
★	Accept USD 20				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Reserved					ON							
★	Reserved					OFF							
	Harness Disable						ON						
★	Harness Enable						OFF						
	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	1 Pulse / USD 1								OFF	OFF			
	2 Pulses / USD 1								ON	OFF			
	4 Pulses / USD 1								OFF	ON			
	20 Pulses / USD 1								ON	ON			
★	Pulse Speed	50ms LO / 50ms HI										OFF	OFF
		60ms LO / 300ms HI										ON	OFF
		30ms LO / 50ms HI										OFF	ON
		150ms LO / 150ms HI										ON	ON

◆ Factory configuration has all switches in the OFF position.

★ Manufacture setting

V7-USD4(Pulse/ICT004/MDB)

V7 Interface Settings: 3 (ICT004)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
	MDB Interface		OFF	OFF	
★	ICT004 Interface		OFF	ON	
	Reserved		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

V7 Interface Settings: 3 (Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	MDB Interface		OFF	OFF	
	ICT004 Interface		OFF	ON	
	Reserved		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

V7 Interface Settings: 3 (MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
★	MDB Interface		OFF	OFF	
	ICT004 Interface		OFF	ON	
	Reserved		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT004	Pulse	MDB
BV1	USD 1	USD 1	USD 1
BV2	USD 5	USD 5	Reserved
BV3	USD 10	USD 10	USD 5
BV4	USD 20	USD 20	USD 10
BV5			USD 20

Note: 1.Default setting.
2.Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.
3.Remove the front cover and the dip-switch in on the CPU board.
(Please refer to "Sw1" setting.)