

V7P-UCD11

V7P Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill CAD 5, 10, 20, 50, 100 5bills.
USD 1, 5, 10, 20, 50, 100 6bills.

V7P dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject CAD 5 & 10 & 20	ON											
★	Accept CAD 5 & 10 & 20	OFF											
★	Reject CAD 50 & 100		ON										
★	Accept CAD 50 & 100		OFF										
★	Reject USD 1 & 5			ON									
★	Accept USD 1 & 5			OFF									
★	Reject USD 10 & 20				ON								
★	Accept USD 10 & 20				OFF								
★	Reject USD 50 & 100					ON							
★	Accept USD 50 & 100					OFF							
★	Reserved						ON						
★	Reserved						OFF						
★	Harness Disable							ON					
★	Harness Enable							OFF					
★	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / CAD 1 & USD 1									OFF	OFF		
★	2 pulses / CAD 1 & USD 1									ON	OFF		
★	4 pulses / CAD 1 & USD 1									OFF	ON		
★	20 pulses / CAD 1 & USD 1									ON	ON		
★	Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

Note : (1) Dip Switch 1 is for Pulse

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(4) 1 USD = 1 CAD

V7P-UCD11(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
★	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Mode		OFF	OFF	
	ICT104V Mode		OFF	ON	
★	MDB Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	MDB	Pulse
BV1	CAD 5	CAD 5	CAD 5	CAD 5
BV2	CAD 10	CAD 10	CAD 10	CAD 10
BV3	CAD 20	CAD 20	CAD 20	CAD 20
BV4	CAD 50	CAD 50	CAD 50	CAD 50
BV5	CAD 100	CAD 100	CAD 100	CAD 100
BV6	USD 1	USD 1	USD 1	USD 1
BV7	USD 5	USD 5	USD 5	USD 5
BV8	USD 10	USD 10	USD 10	USD 10
BV9	USD 20	USD 20	USD 20	USD 20
BV10	USD 50	USD 50	USD 50	USD 50
BV11	USD 100	USD 100	USD 100	USD 100