

BRV-PUN5(PEN3+USD2)

BRV Option Switch Settings: 1(ICT-BC/MDB/VCCS Dummy)

Supported bill PEN 10, 20, 50 3bills. USD 1, 5 2bills.

BRV dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
Reject PEN 10	ON											
Accept PEN 10	OFF											
Reject PEN 20		ON										
Accept PEN 20		OFF										
Reject PEN 50			ON									
Accept PEN 50			OFF									
Reject USD 1 (Note.3)				ON								
Accept USD 1 (Note.3)				OFF								
Reject USD 5 (Note.3)					ON							
Accept USD 5 (Note.3)					OFF							
Normal						OFF	OFF					
Load Banknote to Recycle						ON	OFF					
Load Banknote to Stacker						OFF	ON					
Unload Banknote to Stacker						ON	ON					
Reserved								ON				
Reserved								OFF				
MDB Mode	SW1	SW2	SW3	SW4	VCCS Dummy Mode							
Reserved	ON				★ 255 Bank Note Limitation Per Transaction	ON	ON	ON				
Reserved	OFF				1 Bank Note Limitation Per Transaction	OFF	OFF	OFF				
Reserved		ON			2 Bank Note Limitation Per Transaction	ON	OFF	OFF				
Reserved		OFF			3 Bank Note Limitation Per Transaction	OFF	ON	OFF				
Reserved					4 Bank Note Limitation Per Transaction	ON	ON	OFF				
Reserved					5 Bank Note Limitation Per Transaction	OFF	OFF	ON				
Reserved					6 Bank Note Limitation Per Transaction	ON	OFF	ON				
Reserved					7 Bank Note Limitation Per Transaction	OFF	ON	ON				
Virtual MDB Recycler Function				ON	No Refund After the Deal							ON
Standard MDB Recycler Function				OFF	★ Refund After the Deal							OFF

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses, you should reset the bill acceptor again.

(2) Please reset the bill acceptor after set the dip switch.

(3) Exchange Rate on USD to PEN is 1:3 for MDB Mode)

(4) Calibrate card.

(5) Recycled Banknote represents virtual MDB coin type.

BRV-PUN5(PEN3+USD2)(ICT-BC/MDB/VCCS Dummy)

Interface Settings: 2(ICT-BC)

INTERFACE	SW5	SW6	SW7	SW8
Reserved	ON			
Reserved	OFF			
Connect with MDB Connector		ON		
Connect with RS232 Connector		OFF		
MDB Mode			OFF	OFF
VCCS Dummy Mode			OFF	ON
Reserved			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(VCCS Dummy)

INTERFACE	SW5	SW6	SW7	SW8
Escrow (VCCS Dummy Mode)	ON			
No Escrow (VCCS Dummy Mode)	OFF			
Reserved		ON		
Reserved		OFF		
MDB Mode			OFF	OFF
VCCS Dummy Mode			OFF	ON
Reserved			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

INTERFACE	SW5	SW6	SW7	SW8
Scaling Factor (SF)= 100 Decimal Point Position (DPP)= 2	ON			
Scaling Factor (SF)= 1 Decimal Point Position (DPP)= 0	OFF			
Reserved		ON		
Reserved		OFF		
MDB Mode			OFF	OFF
VCCS Dummy Mode			OFF	ON
Reserved			ON	OFF
ICT-BC Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	VCCS Dummy	ICT-BC	MDB
BV1	PEN 10	PEN 10	PEN 10
BV2	PEN 20	PEN 20	PEN 20
BV3	PEN 50	PEN 50	PEN 50
BV4	USD 1	USD 1	USD 1
BV5	USD 5	USD 5	USD 5