

L70-USD6

L70/P5 DIP SWITCHES SETTING : 1(Pulse/RS232 A0/V2.2)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / USD 1	OFF	OFF	OFF							
	2 Pulses / USD 1	OFF	OFF	ON							
	3 Pulses / USD 1	OFF	ON	OFF							
	4 Pulses / USD 1	OFF	ON	ON							
	5 Pulses / USD 1	ON	OFF	OFF							
	10 Pulses / USD 1	ON	OFF	ON							
	20 Pulses / USD 1	ON	ON	OFF							
	100 Pulses / USD 1	ON	ON	ON							
	Fast output Pulse Lo= 30ms Hi= 50ms				ON						
★	Slow output Pulse Lo= 50ms Hi=100ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept USD 1						ON				
	Reject USD 1						OFF				
★	Accept USD 5							ON			
	Reject USD 5							OFF			
★	Accept USD 10								ON		
	Reject USD 10								OFF		
★	Accept USD 20									ON	
	Reject USD 20									OFF	
★	Accept USD 50 & 100										ON
	Reject USD 50 & 100										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only for Pulse mode.

L70-USD6(Pulse/RS232 A0/V2.2)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	RS232 A0 Mode		ON	ON	
	V2.2 Mode		OFF	ON	
	Reserved		OFF	OFF	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON	OFF	
★	RS232 A0 Mode		ON	ON	
	V2.2 Mode		OFF	ON	
	Reserved		OFF	OFF	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	RS232 A0	V2.2
BV1	USD 1	USD 1	USD 1
BV2	USD 5		USD 5
BV3	USD 10	USD 5	USD 10
BV4	USD 20	USD 10	USD 20
BV5	USD 50	USD 20	USD 50
BV6	USD100	USD 50	USD100
BV7		USD100	

DIP SWITCHES SETTING : 2(V2.2)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON	OFF	
★	RS232 A0 Mode		ON	ON	
	V2.2 Mode		OFF	ON	
	Reserved		OFF	OFF	
	Disable Inverse Mode				ON
★	Enable Inverse Mode				OFF

★ Manufacture setting

RS232 A0 INFORMATION BillType Data	
Code	Denomination
1	USD 1
2	Reserved
3	USD 5
4	USD 10
5	USD 20
6	USD 50
7	USD 100
8	Reserved
9	Reserved