

NE77-USD3

NE77 DIP SWITCHES SETTING : (Pulse/MDB/ICT104U)

Supported bill USD 1, 5, 10 3bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Accept USD 1	ON									
	Reject USD 1	OFF									
★	Accept USD 5		ON								
	Reject USD 5		OFF								
★	Accept USD 10			ON							
	Reject USD 10			OFF							
★	Reserved				ON						
	Reserved				OFF						
★	Reserved					ON					
	Reserved					OFF					
★	Reserved						ON				
	Reserved						OFF				
★	Inhibit level Active Low	Scaling Factor (SF) =100 (MDB only) Decimal Point Position (DPP) = 2						ON			
	Inhibit level Active High	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0						OFF			
★	Pulse Normal High								ON		
	Pulse Normal Low								OFF		
★	MDB Mode									OFF	OFF
	Reserved									OFF	ON
	ICT104U Mode									ON	OFF
	Pulse Mode									ON	ON

(★) Manufacture setting

Note.(1) Please reset the bill acceptor after set the dip switch.
(2) Pulse speed is LO=50ms/HI=100ms.

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U
BV1	USD 1	USD 1	USD 1
BV2	USD 5	USD 5	USD 5
BV3	USD 10	USD 10	USD 10