

S7A II-USD6 Option Switch Settings (Pulse/MDB/ICT104U/Parallel A3)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject USD 1 & 5	ON											
	Accept USD 1 & 5	OFF											
★	Reject USD 10 & 20		ON										
	Accept USD 10 & 20		OFF										
★	Reject USD 50 & 100			ON									
	Accept USD 50 & 100			OFF									
★	High Acceptance				ON								
	High Security				OFF								
★	Reserved					ON							
	Reserved					OFF							
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★	Harness Disable							ON					
	Harness Enable							OFF					
★	Other Interface	Test Mode (No Communication)							ON				
		Operation Mode							OFF				
★	Pulse Mode	Inhibit Active HIGH (Test)							ON				
		Inhibit Active LOW							OFF				
★	ENABLE IrDA Download									ON			
	Reserved									OFF			
★	ENABLE INHIBIT-Sleep Only										ON		
	5 second Timeout Only										OFF		
★	NORMAL											OFF	OFF
	MODE1											OFF	ON
	MODE2											ON	OFF
	MODE1+2											ON	ON

★ Manufacture setting

Note: After setting dip switch of the credit pulses, you should reset the bill acceptor again.

NORMAL : No sleep function.

MODE 1 : Bill-acceptor wakes up VMC with banknote only (special cable required).

MODE 2 : VMC wakes up bill-acceptor.

MODE 1+2 : Bill-acceptor wakes up with banknote or by VMC.

S7A II-USD6(Pulse/MDB/ICT104U/Parallel A3)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / USD 1			OFF	OFF
	2 pulses / USD 1			OFF	ON
	4 pulses / USD 1			ON	OFF
	20 pulses / USD 1			ON	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
	ICT104U			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
★	ICT104U			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(Parallel A3)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
	ICT104U			OFF	ON
	Reserved			ON	ON
★	Parallel A3			ON	OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	Parallel A3
BV1	USD 1	USD 1	USD 1	USD 1
BV2	USD 5	USD 5	USD 5	USD 5
BV3	USD 10	USD 10	USD 10	USD 10
BV4	USD 20	USD 20	USD 20	USD 20
BV5	USD 50	USD 50	USD 50	
BV6	USD 100	USD 100	USD 100	