

TAO-V+MXN9

TAO-V Option Switch Settings: 1(Pulse/MDB)

Supported bill MXN 20, 50, 100, 200, 500
USD 1, 5, 10, 20 9bills.

TAO-V dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject MXN 20 & USD 1	ON											
	Accept MXN 20 & USD 1	OFF											
★	Reject MXN 50 & USD 5		ON										
★	Accept MXN 50 & USD 5		OFF										
★	Reject MXN 100 & USD 10			ON									
★	Accept MXN 100 & USD 10			OFF									
★	Reject MXN 200 & MXN 500 & USD 20				ON								
★	Accept MXN 200 & MXN 500 & USD 20				OFF								
	Accept Mexico Pesos and US Dollars (Note 3)				ON								
★	Accept Mexico Pesos Only (Note 3)				OFF								
★	Reserved				ON								
★	Reserved				OFF								
	Pulse Mode	Other Mode											
	Harness Disable	BA stops working when fishing			ON								
★	Harness Enable	Normal			OFF								
	Inhibit Active High				ON								
★	Inhibit Active Low				OFF								
★	1 pulse / MXN 10 & USD 1								OFF	OFF			
	2 pulses / MXN 10 & USD 1								ON	OFF			
	5 pulses / MXN 10 & USD 1								OFF	ON			
	10 pulses / MXN 10 & USD 1								ON	ON			
★	Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF	
		60ms LO / 300ms HI									ON	OFF	
		30ms LO / 50ms HI									OFF	ON	
		150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

Note : (1) Default setting

(2) Use 2nd dip switch of the internal dip-switch to change different interface protocol.

(3) For Accepting US Dollars, make sure you have dip 5 set to ON position.

(* Exchange Rate on USD to MXN is 1:15 for MDB Mode)

TAO-V+MXN9(Pulse/MDB)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Interface Settings: 2(MDB)

	INTERFACE	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	OFF			
★	Pulse Mode		ON		
★	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB
BV1	USD 1	USD 1
BV2	MXN 20	MXN 20
BV3	MXN 50	MXN 50
BV4	MXN 100	MXN 100
BV5	MXN 200	MXN 200
BV6	MXN 500	MXN 500
BV7	USD 5	USD 5
BV8	USD 10	USD 10
BV9	USD 20	USD 20